

grandMA2 light

SV, silent version



- Real-time control for up to 65,536 parameters per session in connection with MA NPU (equivalent to 256 DMX universes)
- 4,096 HTP/LTP parameters
- 6 DMX outputs
- 2 internal TFT wide mode touchscreens (15.4" WXGA)
- 2 external TFT screens can be connected (UXGA, touchscreens accepted)
- 1 internal command screen – multi-touch (9" SVGA)
- 15 motorized executor faders
- Integrated keyboard drawer
- Built-in uninterruptible power supply (UPS)
- 2 etherCON connectors, 5 USB 2.0 connectors
- Motorized monitor wing
- 2 motorized A/B fader (100mm)
- Individually backlit and dimmable silent (clickless) keys

The grandMA2 light has 4,096 parameters, 15 motorized executor faders and two touchscreens available. All further features and controls are identical to those on the grandMA2 full-size.

The grandMA2 light is the perfect tool to control all kinds of lighting genres like conventionals, moving lights, LEDs, video and media. It supplies an intuitive and fast control of all connected fixtures and channels. The grandMA2 light can handle an almost infinite number of presets, cues, pages, sequences and effects. It is ideally suited as a standalone console or as a backup device for the grandMA2 full-size. Moreover grandMA 'series 1'-showfiles can be converted to be used with the grandMA2.

The "silent version" is equipped with an optimised fan and therefore ideally suited for noise-sensitive environments. It fulfills the international standards NC-25 (Noise Criteria, US) and NR-25 (Noise Rating, Europe).

Scope of delivery

Built-in keyboard

Technical specifications

Dimensions	935 x 204 x 661mm / 36.8 x 8 x 26inch
Operating voltage/ Supply voltage	120V/230V, 50/60Hz (automatic detection)
Net weight	44kg / 97lbs
Power	350VA
Output connectors	6 x XLR 5pin (DMX), 2 x DVI (external Monitor), 2 x etherCON, 1 x MA-Link (grandMA2 fader wing), 2 x USB, 1 x DIN (Midi), 2 x XLR 4pin (Desklight)
Input connectors	1 x XLR 5pin (DMX), 1 x XLR 3pin (Sound), 1 x XLR 3pin (SMPTE), 1 x DIN (Midi), 1 x Sub-D 25pol (Analogue Remote), 1 x powerCON

Article

120112 grandMA2 light

120162 grandMA2 light, SV, silent version

grandMA2 light

SV, silent version



Accessories

120121	grandMA2 fader wing	120122	MA LED desk lamp grandMA2, 4pin, 27"
120132	Dust cover grandMA2 light and ultra-light	121037	MA Case grandMA2 light + ultra-light, with wheels (by Amptown)
121038	MA Case for grandMA2 light and ultra-light, without wheels (by Amptown)	130032	MA NPU (Network Processing Unit)
120142	MA remote control package, incl. Apple iPad® (16GB)	120141	MA remote control package, incl. Apple iPod® touch (8GB)

Additional product pictures

